

ROV USB Programming Guide

OUTLAND CON-500, CON-1050

Outland Technology, Inc. 38190 Commercial Court, Slidell, LA 70458 985-847-1104 sales@outlandtech.com www.outlandtech.com

> Document Number: 42-0026 Rev A3 June 28, 2022

USB Programming Guide

- 1. Install FTDI Chip FT_PRGO (<u>https://ftdichip.com/utilities/</u>) on a computer
- 2. Connect USB Cable from ROV/USB Data Port to Computer
- 3. Open **FT_Prog** App on your computer
- 4. Press the Scan And Parse button

FTDI - FT_Prog						-		×
I EEPROM V FLASH ROM								
FILE DEVICES VIEW HELP								
🗋 😂 🛃 🖻 - 1 👂 🥖 📼								
Device Tree	Property	Value		Information				
Scan and Parse button	No devices			Press the devices	"Scan and Pars	e" button	to find	^
 5. Expand Hardware Specified 6. Set C0 to C3 to the follow C0 = TXLED C1 = TXDEN C2 = RXLED C3 = TXDEN 	fic and Select ving	t CBUS Sigr	nals					
FTDI - FT Prog - Device: 0 [Loc ID:0x12]						-		×
REPROM V FLASH ROM								
FILE DEVICES VIEW HELP								
🗋 🗃 🖬 📲 👂 🎓 Program	m Device							0
	m Device	Value		Information				0
Device Tree Device: 0 [Loc ID:0x12] Device: 0 [Loc ID:0x12]	m Device Property C0	Value	~	Information Hardware	e Specific			0
Image: Second state st	m Device Property C0 C1	Value TXLED TXDEN	~	Information Hardware	e Specific			
□ □ □ □ □ ■	m Device Property C0 C1 C2	Value TXLED TXDEN RXLED	~	Information Hardware IO Contro	e Specific ols:			 • •
Device Tree	m Device Property C0 C1 C2 C3	Value TXLED TXDEN RXLED	~	Information Hardward IO Contro The CBUS	e Specific ols: 6 pins can be inc	dependent	ly	
Image: Second strain strai	m Device Property C0 C1 C2 C3	Value TXLED TXDEN RXLED TXDEN	~ ~ ~	Information Hardward IO Contro The CBUS configured	e Specific o ls: 6 pins can be inc	dependent	ly	
Device Tree	m Device Property C0 C1 C2 C3	Value TXLED TXDEN RXLED TXDEN	~ ~ ~	Information Hardware IO Contro The CBUS configured	e Specific o ls: 6 pins can be inc 1.	dependent	ly	
Device Tree	m Device Property C0 C1 C2 C3	Value TXLED TXDEN RXLED TXDEN	~ ~ ~	Information Hardward IO Contro The CBUS configured	e Specific ols: 6 pins can be inc I.	dependent	ly	
Image: Program Device Tree Image: Program Image: P	m Device Property C0 C1 C2 C3	Value TXLED TXDEN RXLED TXDEN	~ ~ ~	Information Hardward IO Contro The CBUS configured	e Specific o ls: 6 pins can be inc	dependent	ly	
Image: Second state st	m Device Property C0 C1 C2 C3	Value TXLED TXDEN RXLED TXDEN	*	Information Hardward IO Contro The CBUS configured	e Specific ols: 8 pins can be inc 1.	dependent	ly	0
Device Tree	m Device Property C0 C1 C2 C3	Value TXLED TXDEN RXLED TXDEN	~ ~ ~	Information Hardward IO Contro The CBUS configured	e Specific ols: S pins can be inc L	Jependent	ly	
Image: Construction of the second structure Image: Constructure Image: Constructure Image: Constructure Image: Constructure Image: Constructure Image: Constructure Image: Constructure Image: Constructure Image: Constructure Image: Constructure Image: Constructure Image: Constructure Image: C	m Device Property C0 C1 C2 C3	Value TXLED TXDEN RXLED TXDEN	↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓	Information Hardward IO Contro The CBUS configured	e Specific ols: S pins can be inc I.	dependent	ly 	
Device Tree Covice Tree Covice: 0 [Loc ID:0x12] Covice: 0 [Loc ID:0x	m Device Property C0 C1 C2 C3	Value TXLED TXDEN RXLED TXDEN	Program De Device List	Information Hardward IO Contro The CBUS configured	e Specific ols: 6 pins can be inc 1.	dependent	ly –	 x
Program Device Tree Chip Details Order Descriptor USB String Descriptor USB String Descriptor USB String Descriptor Other Advance Specific Other A	m Device Property C0 C1 C2 C3 Sutton	Value TXLED TXDEN RXLED TXDEN	Program De Device Ltt Device 0 [Lc	Information Hardware IO Contro The CBUS configured	Specific Spins can be inc Device Overview Device	dependent	ly 	
Program Device Tree Device: 0 [Loc ID:0x12] TEEPROM Chip Details USB Config Descriptor USB Config Descriptor USB String Descriptors Hardware Specific Port A Battery Charge Detect Invert RS232 Signals Display To Pins 7. Press Program Devices B 8. Program Devices Window	m Device	Value TXLED TXDEN RXLED TXDEN	Program De Device List Device: 0 [Le	Information Hardware IO Contro The CBUS configured	Berice Overview Device Overview Device Overview Device TT	dependent <u>s: 0 (Loc ID:0</u> × Seres'	y 	
Image: Second structure Image: Second structure Image: Second structure Image: Second structure Device Tree Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure Image: Second structure	m Device	Value TXLED TXDEN RXLED TXDEN	Program De Program De Device List Device: 0 [Ls	Information Hardware IO Contro The CBUS configured	Specific Spins can be incl Device Overview Device Chip Type: FT Vendor ID: 0.00 Punded ID: 0.00	Jependent <u>c 0 [Loc ID: (</u> × Seres' 403 015	ly 	
 Program Program Program Program Program Program Program Program Program 	m Device	Value TXLED TXDEN RXLED TXDEN	Program De Device List Device: 0 [Lc	Information Hardward IO Contro The CBUS configured	Device Overview	dependent <u>x: 0 (Loc ID:(</u> X Series' 403 015 Dr	y ▶x12]	
 Program Program Program Program Press Program Device B Program Program Devices Window Program Programing Successful momentarially displayed 	m Device	Value TXLED TXDEN RXLED TXDEN	Program De Device Ltt Device: 0 [Lc	Information Hardward IO Contro The CBUS configured	Pevice Overview Device Overview Device Overview Device Overview Device Product ID: 0.68 Manufacture: FTT Product Description: FT2	e: O [Loc ID:0] X Senes' 403 015 Dr 231X USB UART		
 Program Program Program Program Press Program Device B Program Program Devices Window Program Programing Successful momentarially displayed corner. 	m Device Property C0 C1 C2 C3 Sutton w will open, p ul message w in the bottom	Value TXLED TXDEN RXLED TXDEN	Program De Program De Device List Device: 0 [Le	Information Hardward IO Contro The CBUS configured	Pevice Overview Device Overview Device Overview Device Overview Device Chip Type: TT Vendor ID: 0x8 Manufacture: TTI Product ID: 0x8 Manufacture: T	dependent 2: 0 (Loc ID:0 X Series' 403 015 Dr 131X USB UART 062037 - Fixed	y □ [x12]	
 Program Program Program Press Program Device B Program Devices Window Program Devices Window Program. Programming Sucessful momentarially displayed corner. Device is now ready to u 	m Device	Value TXLED TXDEN RXLED TXDEN	Program De Device List Device: 0 [Lc Select All	Information Hardware IO Contro The CBUS configured	Specific Spins can be inc Spins can be inc Device Overview Device Chip Type: TT Vendor ID: 0x0 Product ID: 0x0 Manufacturer: TTI Product Description: FT2 Sental Number: DNI	dependent <u>e 0 [Loc ID:0</u> X Seres' 403 015 07 123X USB UART 06263T7 - Fixed Only	ly x12]	×
 Program Program Program Program Prot A Battery Charge Detect Invert RS232 Signals OBUS Signals IO Pins 7. Press Program Device B 8. Program Devices Window Program. 9. Programming Sucessful momentarially displayed corner. 10. Device is now ready to u	m Device	Value TXLED TXDEN RXLED TXDEN	Program De Device Utt Device: 0 [Lc Select All Cycle Pots	Information Hardware IO Contro The CBUS configured	Specific Sis: Spins can be incl Device Overview Device Chip Type: TT Vendor ID: 0.00 Manufacture: TTI Product ID: 0.00 Manufacture: TTI Product Description: FT2 Senal Number: DNM	dependent 2: 0 [Loc ID:0 X Seres' 403 015 Dr 231X USB UART 0625GT7- Fixed 0 my gram Err	ly – C bx12] Program Blar Isse	