

SMART CAMERA COMPATIBILITY AND REQUIREMENTS.



Console Model		UWC-425	UWC-430
		(SD Camera)	(HD Camera)
SD Consoles	CON-3300 ¹	6200 Overlay & Adapter Cable 25-0077	NO
	CON-3400 ¹	6200 Overlay & Adapter Cable 25-0077	NO
	CON-3400/D ^{1&2}	6200 Overlay & Adapter Cable 25-0077	NO
HD Consoles	CON-3470	6200 Overlay & Adapter Cable 25-0077	6200 Overlay & Adapter Cable 25-0076
	CON-3470/D ^{4&5}	6200 Overlay & Adapter Cable 25-0077	6200 Overlay & Adapter Cable 25-0076
	CON-3500/D ^{3,4&5}	6200 Overlay & Adapter Cable 25-0077	6200 Overlay & Adapter Cable 25-0076

Console Specific Notes:

- SD consoles WITH internal VTW option manufactured prior to January 2020 may be returned to Outland for reprogramming. If re-programmed, they do NOT require 6200 Overlay or 25-0077 cable adapter. Contact Outland to verify compatibility.
- SD dual consoles may use dual smart cameras by using two 6200 Overlays. Per note 1, if VTW consoles are reprogrammed by Outland, only one 6200 Overlay & Adapter Cable 25-0077 would be required to have dual smart cameras.
- CON-3500/D consoles with 15 pin D-Sub connection only require 6200 Overlay and does not require 25-0076 or 25-0077 Cable adapters. An RCA cable (not included), from the Overlay 6200 to the back of the HD DVR is required on all consoles prior to January 2020.
- Only HD consoles with OTI-1080-4C DVRs will work with the smart cameras, older DVRs are not compatible. Firmware version 3.44.200TLN01 is the oldest version that will support Smart Camera Overlay. Direction to update the DVR and the current firmware can be found at [OTI-1080-AC](#).
- HD, dual consoles, will only support “smart” camera functions on the Diver 1 channel.

General Notes:

- Consoles with “/E” or “/DC” options does not affect compatibility.
- Camera format must match console format. For example, if console is PAL video system (“/E”), camera must also be PAL (“/E”)